

MonoDAQ-E-gMeter

A data acquisition device with embedded triaxial MEMS accelerometer, analog-to-digital conversion and EtherCAT interface based on the MonoDAQ EtherCAT platform (www.monodaq.com).



Specifications of the MEMS accelerometer:

| | Min. | Typ. | Max. | Unit |
|---|-------|---------|------|--------|
| Measurement ranges | + -2 | | + -8 | g |
| -3 dB bandwidth | | 1000 | | Hz |
| Noise density (+ -2 g) | | 25 | | ug√Hz |
| Offset error | -75 | + -25 | +75 | mg |
| Offset temp. drift (-40...125 degC) | -0.15 | + -0.02 | 0.15 | mg/C |
| Sensitivity temp. drift (-40...125 degC) | | + -0.01 | | %/degC |
| Linearity error -1g ... +1g range | | 0.1 | | % FS |
| Crossaxis sensitivity | -1 | | +1 | % |

Specifications of the MonoDAQ-E-gMeter device:

| | |
|------------------------------|-----------------|
| Digital interface | EtherCAT |
| Interface connectors | RJ45 |
| Power consumption | 1300 mW |
| Supply voltage | 12-48 V |
| Operating temperature | -20 ... 60 degC |
| IP rating | IP20 |

Software support: DEWESoft X3, any standard EtherCAT master

Installation: Devices are daisy chained with a standard network cable. It is recommended that the cable is shielded (SFTP, CAT5e) and has a minimum 24 AWG wire thickness. The cable must have 4 wire pairs. The maximum distance node-to-node is 50 m.

Power supply: Passive PoE power injector is necessary for merging the EtherCAT signal and power into a single cable.

| Power supply voltage | Cable length device-to-device | Cable size | Max. number of devices from a single power supply |
|----------------------|-------------------------------|------------|---|
| 24 V | 1 m | AWG 24 | 8 |
| 24 V | 50 m | AWG 24 | 4 |
| 48 V | 1 m | AWG 24 | 12 |
| 48 V | 50 m | AWG 24 | 10 |