



Main

Range	TeSys
Product or component type	Auxiliary contact block
Product compatibility	GV7RE GV7RS

Complementary

Auxiliary contacts operation	Standard
Pole contact composition	1 C/O
[Ui] rated insulation voltage	690 V - for control circuit - conforming to IEC 60947-1
System Voltage	110 V AC control circuit 110 V DC control circuit 230...240 V AC control circuit 24 V AC control circuit 24 V DC control circuit 250 V DC control circuit 380...415 V AC control circuit 440 V AC control circuit 48 V AC control circuit 48 V DC control circuit 690 V AC control circuit
Mechanical durability	50000 cycles
Minimum switching current	5 mA control circuit
Minimum switching voltage	17 V control circuit
Connections - terminals	Control circuit: connector 1 cable 0 in ² (1.5 mm ²) - cable stiffness: flexible - with cable end Control circuit: connector 1 cable 0 in ² (1.5 mm ²) - cable stiffness: flexible - without cable end Control circuit: connector 1 cable 0 in ² (1.5 mm ²) - cable stiffness: solid
Product weight	0.03 lb(US) (0.015 kg)

Environment

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 0744 - Schneider Electric declaration of conformity	Compliant - since 0744 - Schneider Electric declaration of conformity
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.	Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.