

CRD

CRD is used for current stabilization and current limiting.

□ 102 □



102

- Packing condition
 - None : E Series, Individually packed in a bag
 - 26Z : E Series, 26mm wide axial taping winding type
 - 26R : E Series, 26mm wide axial taping role type
 - 52Z : E Series, 52mm wide axial taping winding type
 - 52R : E Series, 52mm wide axial taping role type
 - RE : E Series, Radial taping winding type
 - T : S Series, Taping role
- Pinch off current
 - e.g.) : 301⇒ $30 \times 10^1 \mu A = 0.3mA$
 - 102⇒ $10 \times 10^2 \mu A = 1.0mA$
 - 452⇒ $45 \times 10^2 \mu A = 4.5mA$
- E : Lead wire type
- S : SMD type

Graph of Current (mA) vs. Voltage (V) for an n-channel JFET. The curve shows the relationship between gate-source voltage and drain current. Key points marked include $V_{GS(off)}$ (pinch-off voltage), V_{GS} (gate-source voltage), $V_{GS(th)}$ (threshold voltage), and I_{SS} (saturation current). The current increases linearly from $V_{GS(th)}$ to $V_{GS(off)}$ and then levels off at I_{SS} .

	E series	S series
Rating power	300mW	500mW
Rated voltage (Pulse wave)	100V(E-101~E-562) 50V(E-822~E-183)	100V(S-101T~S-562T) 50V(S-822T~S-183T)
Reverse current	50mA	
Junction temp	150°C	
Operating temp	-30°C~150°C	-40°C~150°C




Part No.	Voltage	Part No.	Voltage
E101~E-562	100V	S-101T~S-562T	100V
E-822	30	S-822T	50
E-103		S-103T	
E-123		S-123T	
E-153	25	S-153T	40
F-183		S-183T	



Part No.		Pinch-off current ^{*1}		Limiting current ^{*2}		Limiting current ratio $I_{100V}/I_p^* I_{30V}/I_p$	Temperature ^{*3} Coefficient (% / °C)
SMD	With Lead	Test Voltage	$I_p(\text{mA})$ Typical	min~max	$V_K(V)$		
S-101T	E-101	10V	0.10	0.05~0.21	0.5	1.1max	+2.10~-+0.10
S-301T	E-301		0.30	0.20~0.42	0.8		+0.40~-0.20
S-501T	E-501		0.50	0.40~0.63	1.1		+0.15~-0.25
S-701T	E-701		0.70	0.60~0.92	1.4		0.00~-0.32
S-102T	E-102		1.00	0.88~1.32	1.7		-0.10~-0.37
S-152T	E-152		1.50	1.28~1.72	2.0		-0.13~-0.40
S-202T	E-202		2.00	1.68~2.32	2.3		-0.15~-0.42
S-272T	E-272		2.70	2.28~3.10	2.7		-0.18~-0.45
S-352T	E-352		3.50	3.00~4.10	3.2		-0.20~-0.47
S-452T	E-452		4.50	3.90~5.10	3.7		-0.22~-0.50
S-562T	E-562		5.60	5.00~6.50	4.5		-0.25~-0.53
S-822T	E-822		8.20	6.56~9.84	3.1		-0.25~-0.45
S-103T	E-103		10.0	8.00~12.0	3.5		-0.25~-0.45
S-123T	E-123		12.0	9.60~14.4	3.8		-0.25~-0.45
S-153T	E-153		15.0	12.0~18.0	4.3		-0.25~-0.45
S-183T	E-183		18.0	16.0~20.0	4.6		-0.25~-0.45
						*1.0max	

*I30/Ip

There are three Types for taping.




*In principal elements are set with cathode side on the round hole side.


Type 1 Roll.....5000pcs
Box.....2500pcs

Type 2	4000pcs
Type 3	3000pcs

Power derating



Pinch-off current Temperature




CRD in parallel

The use of CRD in parallel increases their current handling capabilities.

Increasing the voltage range using a zener diode


Connecting zener diodes in series with the line ensures that the current is constant in high-voltage area.




The compensation of current reduction due to self heating

Placing resistors in parallel with CRD can correct any current decrease when the applied voltage increases. The following values are typical for correction resistors.

E-102	1M Ω	E-352	82k Ω
E-152	390k Ω	E-452	56k Ω
E-202	240k Ω	E-562	39k Ω
E-272	120k Ω		



Compensative resistor is not necessary if the current value is less than 1 mA.



Dynamic characteristics (saturation characteristics)

