



Main

| | |
|---------------------------------------|---|
| Range of product | Altivar |
| Range compatibility | Altivar 312 Altivar 61 Altivar 71 Altivar 32 Altivar 212 Altivar Lift Altivar 61Q Altivar 71Q Altivar 312 Solar Altivar Machine ATV320 |
| Accessory / separate part category | Display and signalling accessories |
| Accessory / separate part type | Display terminal |
| Accessory / separate part destination | Variable speed drive |
| Product specific application | To control, adjust and configure the drive To display the current values To save and download configurations |
| IP degree of protection | IP54 |

Complementary

| | |
|---------------------------|--|
| Mounting location | On the door of an enclosure |
| User language | Chinese English French German Italian Spanish |
| Messages display capacity | 8 lines |
| Pixel resolution | 240 x 160 |
| Product weight | 0.32 lb(US) (0.145 kg) |

Environment

| | |
|---------------------------------------|------------------------------|
| ambient air temperature for operation | > 5...122 °F (> -15...50 °C) |
|---------------------------------------|------------------------------|

Offer Sustainability

| | |
|--|--|
| WARNING: This product can expose you to chemicals including: | WARNING: This product can expose you to chemicals including: |
| Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. | Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. |
| Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. | Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. |
| For more information go to www.p65warnings.ca.gov | For more information go to www.p65warnings.ca.gov |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.