



## Main

Range of product	Altivar
Product or component type	ATV71 hoist resistor
Range compatibility	Altivar 71
Product compatibility	ATV71HD15N4 ATV71HD15Y ATV71HD18N4 ATV71HD18Y ATV71HD22N4 ATV71HD22Y ATV71HD30N4 ATV71HD30Y ATV71HU55M3 ATV71HU75M3 ATV71WD15N4 ATV71WD18N4 ATV71WD22N4 ATV71WD30N4
Average power available	22.4 kWat 122 °F (50 °C)
Ohmic value	14 Ohm

## Complementary

Electrical connection	Bar wire with M10 screw
Protection type	Thermal protection via thermal overload relay
Product weight	119.05 lb(US) (54 kg)

## Environment

ambient air temperature for operation	32...122 °F (0...50 °C)
ambient air temperature for storage	-13...167 °F (-25...75 °C)
IP degree of protection	IP23

## Offer Sustainability

WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm.	Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm.
For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>	For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>

## Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.