PLR SERIES

8-PIN

Description

The PLR Series provides a cost effective means of preventing 3-phase motor startup during adverse voltage conditions. Proper A-B-C sequence must occur in order for the PLR's output contacts to energize. In addition, the relay will not energize when an undervoltage or phase loss condition is present. The PLR Series protects a motor against undervoltage operation. The adjustment knob sets the undervoltage trip point.

Operation

The output relay is energized and the LED glows when all voltages are acceptable and the phase sequence is correct. Undervoltage must be sensed for a continuous dropout delay period before the relay de-energizes. Reset is automatic upon correction of the fault condition. The output relay will not energize if a fault condition is sensed as power is applied.

Field Adjustment: Turn the adjustment knob fully counterclockwise and apply three-phase power. The LED should be ON. Increase adjustment until the LED goes OFF. Decrease adjustment until LED glows again. If nuisance tripping occurs, decrease the adjustment slightly.

NOTE: When properly adjusted and operating in an average system, a voltage unbalance of 10% or more is required for phase loss detection. When a phase is lost while the motor is running, a voltage will be induced into the open phase nearly equal in magnitude to the normal phase-to-phase voltage. This condition is known as regeneration. When regenerated voltages are present, the voltage unbalance during single phasing may not exceed 10% for some motors. The PLR Series may not provide protection under this condition. For systems that require superior phase loss protection, select the PLMU Series.

Wiring Diagram



F = Fuses
ØA = Phase A = L1
ØB = Phase B = L2
ØC = Phase C = L3
NO = Normally Open
NC = Normally Closed

Relay contacts are isolated

2A fast acting fuses recommended for safety (not required).

Features & Benefits

FEATURES	BENEFITS
Continuous monitoring	Prevents 3-phase motor startup when undervoltage or phase loss condition is present
Industry standard 8-pin octal plug connection	Eliminates need for special connectors
LED indication	Quick visual indication of output status and correct phase sequence

Ordering Information

MODEL	LINE VOLTAGE
PLR120A	95 to 140VAC
PLR240A	190 to 270VAC
PLR380A	340 to 450VAC
PLR480A	380 to 500VAC

If you don't find the part you need, call us for a custom product 800-843-8848

© 2016 Littelfuse Protection Relays & Controls

PLR SERIES

Accessories

BZ1 Front Panel Mount Kit
Provides an easy method of through-the-panel mounting of 8- or 11-pin plug-in timers, flashers, and other controls.

OT08PC Octal 8-pin Socket
8-pin 35mm DIN rail or surface mount. Rated at 10A @ 600VAC. Surface mounted with two #6 screws or snaps onto a 35 mm DIN rail.

LPSM003ZXID (Indicating), LPSM003Z (Non-indicating) Fuse Holders
Littelfuse POWR-SAFE Dead Front holders provide optimum protection to personnel for Class CC and Midget-Style fuses. 600 VAC/DC

0KLK002.T Midget Fuse (2 Amp)
10 x 38 fast acting, high-interrupting capacity, current-limiting type fuse. 600 Vac/500 Vdc

C103PM (AL) DIN Rail
35 mm aluminum DIN rail available in a 36 in. (91.4 cm) length.

Specifications

Line Voltage

Type	3-phase delta or wye with no connection to neutral

Nominal Voltage	**Undervoltage Dropout Adj. Range**	**Line Voltage Max.**
120VAC	85 to 130VAC	143VAC
240VAC	170 to 240VAC	270VAC
380VAC	310 to 410VAC	480VAC
480VAC	350 to 480VAC	530VAC

AC Line Frequency	50/60Hz
Phase Sequence	ABC
Response Times	
Pull-in	≤ 400ms
Drop-out	≤ 100ms
Hysterisis	
Pull-in/Drop-out	≅ 2%
Output	
Type	Electromechanical relay, energized when all voltages are acceptable
Form	SPDT
Rating	5A resistive @ 240VAC, 1/4 Hp @ 120VAC
Maximum Voltage	250VAC
Protection	
Phase Reversal/Failure	ASME A17.1 Rule 210.6
Motors and Generators	NEMA MG1 14:30, 14:35
Surge	IEEE C62.41-1991 Level B
Isolation Voltage	
120 & 240VAC	≥ 1500V RMS input to output
380 & 480VAC	≥ 2500V RMS input to output
Mechanical	
Dimensions	**H** 81.3 mm (3.2"); **W** 60.7 mm (2.39"); **D** 45.2 mm (1.78")
Mounting*	Plug-in socket
Termination	Octal 8-pin, plug-in
Environmental	
Operating/Storage Temperature	0° to 55°C / -40° to 85°C
Weight	≅ 6 oz (170 g)

*CAUTION: Select an octal socket rated for 600VAC operation.

© 2016 Littelfuse Protection Relays & Controls