

CW Series LTE Band 14 Single-Band Connectorized Monopole Antenna

CW Series antennas are rugged, low-cost and easy to install. The single frequency band of CW antennas makes the job of antenna selection simple, with better performance in the target frequency band than in multiband antennas and rejection of signals from unwanted frequencies.

The CW LTE Band 14 antenna targets 750 MHz to 800 MHz with excellent VSWR, gain and efficiency for LTE Band 14 and FirstNet® Public Safety applications.

This rugged 1/4-wave monopole antenna may be used with plastic or metal enclosures and supports weather-resistant applications.



Features

- Outperforms similar multiband solutions
- Durable, flexible main shaft
- Weather resistant for IP-rated applications¹
- Wide bandwidth
- O-ring compatible base
- Compatible with plastic² and metal enclosures
- High gain (1.1 dBi at 750 MHz, 1.8 dBi at 778 MHz and 1.3 dBi at 800 MHz)
- High efficiency (70% at 750 MHz, 78% at 778 MHz and 72% at 800 MHz)

Applications

- LTE Band 14
- FirstNet® Public Safety
- LTE-M (Cat-M1) and NB-IoT devices
- Hand-held devices
- Internet of Things (IoT) devices

Ordering Information

Part Number	Description
ANT-B14-CW-QW-SMA	LTE Band 14 CW Series antenna with SMA connector

Available from Linx Technologies and select distributors and representatives.

Notes

¹ Use of an O-ring is recommended, IP-ratings cannot be guaranteed

² With appropriate counterpoise

Electrical Specifications

	ANT-B14-CW-QW-SMA
Frequency Range	750 MHz to 800 MHz
Center Frequency	778 MHz
VSWR	$\leq 2.0 : 1$
Peak Gain	1.9 dBi
Polarization	Linear
Radiation	Omnidirectional
Max Power	10 W
Wavelength	1/4-wave
Impedance	50 Ω
Connection	SMA plug (male)
Height	94.2 mm (3.71 in)
Weight	13.6 g (0.48 oz)
Operating Temperature	-40 °C to +90 °C

Electrical specifications and plots measured with a 102 mm x 102 mm (4 in x 4 in) reference ground plane.

VSWR

Figure 1 and Figure 2 provide the voltage standing wave ratio (VSWR) across the antenna bandwidth. VSWR describes the power reflected from the antenna back to the radio. A lower VSWR value indicates better antenna performance at a given frequency. Reflected power is also shown on the right-side vertical axis as a gauge of the percentage of transmitter power reflected back from the antenna.




Figure 1. CW LTE Band 14 Antenna VSWR with Band 14 Uplink/Downlink Highlights




Figure2. CW LTE Band 14 Antenna Full Bandwidth VSWR

Return Loss

Return loss (Figure3), represents the loss in power at the antenna due to reflected signals. Like VSWR, a lower return loss value indicates better antenna performance at a given frequency.




Figure3. CW LTE Band 14 Antenna Return Loss with Band 14 Uplink/Downlink Highlights

Peak Gain

The peak gain across the antenna bandwidth is shown in Figure 4. Peak gain represents the maximum antenna input power concentration across 3-dimensional space, and therefore peak performance, at a given frequency, but does not consider any directionality in the gain pattern.




Figure 4. CW LTE Band 14 Antenna Peak Gain with Band 14 Uplink/Downlink Highlights

Average Gain

Average gain (Figure 5), is the average of all antenna gain in 3-dimensional space at each frequency, providing an indication of overall performance without expressing antenna directionality.




Figure 5. CW LTE Band 14 Antenna Average Gain with Band 14 Uplink/Downlink Highlights

Radiation Efficiency

Radiation efficiency (Figure 6), shows the ratio of power delivered to the antenna relative to the power radiated at the antenna, expressed as a percentage, where a higher percentage indicates better performance at a given frequency.




Figure 6. CW LTE Band 14 Antenna Radiation Efficiency with Band 14 Uplink/Downlink Highlights

Product Dimensions




Figure 7. CW LTE Band 14 Antenna Dimensions

Counterpoise

Quarter-wave or monopole antennas require an associated ground plane counterpoise for proper operation. The size and location of the ground plane relative to the antenna will affect the overall performance of the antenna in the final design. When used in conjunction with a ground plane smaller than that used to tune the antenna, the center frequency typically will shift higher in frequency and the bandwidth will decrease. The proximity of other circuit elements and packaging near the antenna will also affect the final performance.

For further discussion and guidance on the importance of the ground plane counterpoise, please refer to Linx Application Note AN-00501: Understanding Antenna Specifications and Operation.





Figure8. CW LTE Band 14 Antenna Shown On Edge of Evaluation Board

Radiation Patterns

Radiation patterns provide information about the directionality and 3-dimensional gain performance of the antenna by plotting gain at specific frequencies in three orthogonal planes. Antenna radiation patterns (Figure9), are shown using polar plots covering 360 degrees. The antenna graphic above the plots provides reference to the plane of the column of plots below it. Note: when viewed with typical PDF viewing software, zooming into radiation patterns is possible to reveal fine detail.



758 MHz to 798 MHz (778 MHz)




Figure9. Radiation Patterns for CW LTE Band 14 Antenna

Website: <http://linxtechnologies.com>
Linx Offices: 159 Ort Lane, Merlin, OR, US 97532
Phone: +1 (541) 471-6256
E-MAIL: info@linxtechnologies.com

Linx Technologies reserves the right to make changes to the product(s) or information contained herein without notice. No liability is assumed as a result of their use or application. No rights under any patent accompany the sale of any such product(s) or information.

Wireless Made Simple is a registered trademark of Linx Acquisitions LLC. FirstNet is a registered trademark of U.S. Department of Commerce, First Responder Network Authority. Other product and brand names may be trademarks or registered trademarks of their respective owners.

Copyright © 2019 Linx Technologies

All Rights Reserved

Doc # DS19168-09ANT

