DRAWING MADE IN THIRD ANGLE PROJECTION

PART NUMBER	REV	FIRST USED	TERMINATOR	FEED TYPE	DESCRIPTION
1528047-1	C	–	LEADMAKER	MECH POST FEED	CUTS CARRIER
1528047-2	C	–	BENCH	MECH PRE FEED	CUTS CARRIER
1528047-6	C	–	LEADMAKER	MECH POST FEED	CONTINUOUS CARRIER
7-1528047-1	C	–	LEADMAKER	MECH POST FEED	-1 AND SPARE PARTS
7-1528047-2	C	–	BENCH	MECH PRE FEED	-2 AND SPARE PARTS
7-1528047-6	C	–	LEADMAKER	MECH POST FEED	-6 AND SPARE PARTS
7-1528047-7	A	–	–	–	SPARE PARTS KIT

CRIMP DATA AMP TERMINAL AMP CRIMP SPECS

TERMINAL NAME: CONTACT, PIN MOD IV

CRIMP	SIZE	TYPE	RANGE
WIRE	1.07 [.042 IN]	F	26 - 22 AWG
INSUL	1.57 [.062 IN]	O	1.55 MAX [.061 MAX]

WIRE STRIP LENGTH 2.77-4.37 [.109-.172 IN]

APPL INSTRUCTION 408-8322 & 408-8490

TERMINAL – – FEED

APPL SPEC 114-25016 – 7.62 [.300 IN]

TERMINALS APPLIED

102095	–	–	–	–
166678	–	–	–	–
–	–	–	–	–
–	–	–	–	–
–	–	–	–	–
–	–	–	–	–
–	–	–	–	–
–	–	–	–	–

WIRE SIZE mm² AWG	CRIMP HEIGHT *	REF SETTING
22 AWG	0.91 ±0.05 [.036 ±.002 IN]	C 8
24 AWG	0.81 ±0.05 [.032 ±.002 IN]	D 5
26 AWG	0.76 ±0.05 [.030 ±.002 IN]	D 9
–	–	–
–	–	–
–	–	–
–	–	–
–	–	–
–	–	–
–	–	–
–	–	–
–	–	–
–	–	–
–	–	–
–	–	–
–	–	–

1. RECOMMENDED SPARE PARTS.
2. GREASE RAM, CAM, CAM FOLLOWER AND FEED ROD LIGHTLY.
3. LUBRICATE DAILY PER THE APPLICATOR INSTRUCTION SHEET SUPPLIED WITH THE APPLICATOR.
4. CERTAIN TERMINALS REQUIRE LUBRICATION. REFER TO THE APPLICATOR INSTRUCTION SHEET FOR MORE INFORMATION.
5. CUT TO LENGTH AT ASSY.





* WARNING:
ON INSTALLATION, SET WIRE DISC TO LARGEST WIRE SIZE SETTING. USE OF SETTINGS BELOW MIN REQ'D CRIMP HEIGHT SETTING WILL CAUSE DAMAGE TO CRIMP TOOLING.



FENCE SET-UP DIM

| | | | |