LTO 100

RoHS

COMPLIANT



Vishay Sfernice

Power Resistor Thick Film Technology



LTO series are the extension of RTO types. We used the direct ceramic mounting design (no metal tab) of our RCH power resistors applied to semiconductor packages.

FEATURES

• 100 W at 25 °C case temperature heatsink mounted



- Broad resistance range: 0.015 Ω to 1 $M\Omega$
- Non inductive
- TO-247 package: Compact and easy to mount
- Material categorization: For definitions of compliance please see <u>www.vishay.com/doc?99912</u>



Note

• Tolerances unless stated: ± 0.3 mm

STANDARD ELECTRICAL SPECIFICATIONS							
MODEL	SIZE	RESISTANCE RANGE Ω	RATED POWER P _{25 °C} W	LIMITING ELEMENT VOLTAGE U _L V	TOLERANCE ± %	TEMPERATURE COEFFICIENT ± ppm/°C	$\begin{array}{c} \text{CRITICAL} \\ \text{RESISTANCE} \\ \Omega \end{array}$
LTO 100	TO-247	0.015 to 1 M	100	500	1, 2, 5, 10	150, 250, 700, 900	2.5 K

MECHANICAL SPECIFICATIONS			
Mechanical Protection	Molded		
Resistive Element	Thick film		
Substrate	Alumina		
Connections	Tinned copper		
Weight	3.5 g max.		
Mounting Torqure	1 Nm		

ENVIRONMENTAL SPECIFICATIONS			
Temperature Range	- 55 °C to + 175 °C		
Climatic Category	55/175/56		
Flammability	IEC 60695-11-5 2 applications 30 s separated by 60 s		

Onto a heatsink			
100 W at + 25 °C (case temp.) R _{TH (j - c)} : 4.2 °C/W Free air: 2.25 W at + 25 °C			
See Performance table			
± 150 ppm/°C			
1500 V _{RMS} - 1 min 10 mA max.			
$\geq 10^4 \text{ M}\Omega$			
≤ 0.1 μH			

Revision: 21-Jan-13

THIS DOCUMENT IS SUBJECT TO CHANGE WITHOUT NOTICE. THE PRODUCTS DESCRIBED HEREIN AND THIS DOCUMENT ARE SUBJECT TO SPECIFIC DISCLAIMERS, SET FORTH AT <u>www.vishay.com/doc?91000</u>



www.vishay.com

Vishay Sfernice

PERFORMANCE					
TESTS	CONDITIONS	REQUIREMENTS			
Momentary Overload	EN 60115-1 1.5 Pr/5 s U _S < 1.5 U _L	± (0.5 % + 0.005 Ω)			
Load Life	EN 60115-1 1000 h Pr at + 25 °C	± (1 % + 0.005 Ω)			
High Temperature Exposure	AEC-Q200 REV D conditions: MIL-STD-202 method 108 1000 h, + 175 °C, unpowered	± (0.25 % + 0.005 Ω)			
Temperature Cycling	AEC-Q200 REV D conditions: Pre-conditioning 3 reflows according JESTD020D for $R < 10 \Omega$ 500 cycles - 55 °C/+ 125 °C for $R \ge 10 \Omega$ 1000 cycles - 55 °C/+ 125 °C dwell time - 15 min	± (0.5 % + 0.005 Ω)			
Biased Humidity	AEC-Q200 REV D conditions: MIL-STD-202 method 103 1000 h, 85 °C, 85 % RH	± (1 % +0.005 Ω)			
Operational Life	AEC-Q200 REV D conditions: Pre-conditioning 3 reflows according JESTD020D MIL-STD-202 method 108 1000 h, 90/30, powered, + 125 °C	± (1 % +0.005 Ω)			
ESD Human Body Model	AEC-Q200 REV D conditions: AEC-Q200-002 25 kV _{AD}	± (0.5 % +0.005 Ω)			
Vibration	AEC-Q200 REV D conditions: MIL-STD-202 method 204 5 g's for 20 min, 12 cycles test from 10 Hz to 2000 Hz	± (0.5 % +0.005 Ω)			
Mechanical Shock	AEC-Q200 REV D conditions: MIL-STD-202 method 213 100 g's, 6 ms, 3.75 m/s 3 shocks/direction	± (0.5 % +0.005 Ω)			
Terminal Strength	AEC-Q200 REV D conditions: AEC-Q200-006 2 kgf, 60 sec	± (0.25 % +0.01 Ω)			

SPECIAL FEATURES					
Resistance Values	≥ 0.015	≥ 0.1	> 20		
Tolerances	± 1 % at ± 10 %				
Typical Temperature Coefficient (- 55 ° to + 175 °C)	± 900 ppm/°C	± 350 ppm/°C	± 150 ppm/°C		

CHOICE OF THE HEATSINK

The user must choose according to the working conditions of the component (power, room temperature).

Maximum working temperature must not exceed 175 °C. The dissipated power is simply calculated by the following ratio:

$$P = \frac{\Delta T}{[R_{TH (j-c)}] + [R_{TH (c-h)}] + [R_{TH (h-a)}]}^{(1)}$$

P: Expressed in W

 ΔT : Difference between maximum working temperature and room temperature

R_{TH (j - c)}: Thermal resistance value measured between resistive layer and outer side of the resistor. It is the thermal resistance of the component.

R_{TH (c - h}): Thermal resistance value measured between outer side of the resistor and upper side of the heatsink. This is the thermal resistance of the interface (grease, thermal pad), and the quality of the fastening device.

R_{TH (h - a)}: Thermal resistance of the heatsink.

Example:

 $R_{TH (c - h)} + R_{TH (h - a)}$ for LTO 100 power rating 10 W at ambient temperature + 25 °C Thermal resistance $R_{TH (j - c)}$: 1.5 °C/W Considering equation ⁽¹⁾ we have:

 $\begin{array}{l} \Delta T = 175 \ ^{\circ}\text{C} - 25 \ ^{\circ}\text{C} = 150 \ ^{\circ}\text{C} \\ R_{\text{TH} (j - c)} + R_{\text{TH} (c - h)} + R_{\text{TH} (h - a)} = \frac{\Delta T}{P} = \frac{150}{10} = 15 \ ^{\circ}\text{C/W} \\ R_{\text{TH} (c - h)} + R_{\text{TH} (h - a)} = 15 \ ^{\circ}\text{C/W} - 1.5 \ ^{\circ}\text{C/W} = 13.5 \ ^{\circ}\text{C/W} \end{array}$

with a thermal grease $R_{TH (c-h)} = 1 \text{ °C/W}$, we need a heatsink with $R_{TH (h-a)} = 12.5 \text{ °C/W}$.

Revision: 21-Jan-13

2

Document Number: 50051

For technical questions, contact: <u>sfer@vishay.com</u> THIS DOCUMENT IS SUBJECT TO CHANGE WITHOUT NOTICE. THE PRODUCTS DESCRIBED HEREIN AND THIS DOCUMENT ARE SUBJECT TO SPECIFIC DISCLAIMERS, SET FORTH AT <u>www.vishay.com/doc?91000</u>

LTO 100



Vishay Sfernice

OVERLOADS

In any case the applied voltage must be lower than the maximum overload voltage of 750 V.

The values indicated on the graph below are applicable to resistors in air or mounted onto a heatsink.

ENERGY CURVE



POWER CURVE



POWER RATING

The temperature of the case should be maintained within the limits specified.

To improve the thermal conductivity, surfaces in contact should be coated with a silicone grease and the torque applied on the screw for tightening should be around 1 Nm.



PACKAGING	
Tube of 30 units	

MARKING

Model, style, resistance value (in Ω), tolerance (in %), manufacturing date, Vishay Sfernice trademark.

THIS DOCUMENT IS SUBJECT TO CHANGE WITHOUT NOTICE. THE PRODUCTS DESCRIBED HEREIN AND THIS DOCUMENT ARE SUBJECT TO SPECIFIC DISCLAIMERS, SET FORTH AT www.vishay.com/doc?91000

LTO 100



www.vishay.com

Vishay Sfernice

ORDERI	NG INFO	ORMATION					
LTO	100	F	2.7 kΩ	±1%	XXX	TU30	e3
MODEL	STYLE	CONNECTIONS	RESISTANCE VALUE	TOLERANCE	CUSTOM DESIGN	PACKAGING	LEAD (Pb)-FREE
				± 1 % ± 2 % ± 5 % ± 10 %	Optional on request: Special TCR, shape etc.		





Vishay

Disclaimer

ALL PRODUCT, PRODUCT SPECIFICATIONS AND DATA ARE SUBJECT TO CHANGE WITHOUT NOTICE TO IMPROVE RELIABILITY, FUNCTION OR DESIGN OR OTHERWISE.

Vishay Intertechnology, Inc., its affiliates, agents, and employees, and all persons acting on its or their behalf (collectively, "Vishay"), disclaim any and all liability for any errors, inaccuracies or incompleteness contained in any datasheet or in any other disclosure relating to any product.

Vishay makes no warranty, representation or guarantee regarding the suitability of the products for any particular purpose or the continuing production of any product. To the maximum extent permitted by applicable law, Vishay disclaims (i) any and all liability arising out of the application or use of any product, (ii) any and all liability, including without limitation special, consequential or incidental damages, and (iii) any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability.

Statements regarding the suitability of products for certain types of applications are based on Vishay's knowledge of typical requirements that are often placed on Vishay products in generic applications. Such statements are not binding statements about the suitability of products for a particular application. It is the customer's responsibility to validate that a particular product with the properties described in the product specification is suitable for use in a particular application. Parameters provided in datasheets and/or specifications may vary in different applications and performance may vary over time. All operating parameters, including typical parameters, must be validated for each customer application by the customer's technical experts. Product specifications do not expand or otherwise modify Vishay's terms and conditions of purchase, including but not limited to the warranty expressed therein.

Except as expressly indicated in writing, Vishay products are not designed for use in medical, life-saving, or life-sustaining applications or for any other application in which the failure of the Vishay product could result in personal injury or death. Customers using or selling Vishay products not expressly indicated for use in such applications do so at their own risk. Please contact authorized Vishay personnel to obtain written terms and conditions regarding products designed for such applications.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document or by any conduct of Vishay. Product names and markings noted herein may be trademarks of their respective owners.

Material Category Policy

Vishay Intertechnology, Inc. hereby certifies that all its products that are identified as RoHS-Compliant fulfill the definitions and restrictions defined under Directive 2011/65/EU of The European Parliament and of the Council of June 8, 2011 on the restriction of the use of certain hazardous substances in electrical and electronic equipment (EEE) - recast, unless otherwise specified as non-compliant.

Please note that some Vishay documentation may still make reference to RoHS Directive 2002/95/EC. We confirm that all the products identified as being compliant to Directive 2002/95/EC conform to Directive 2011/65/EU.

Vishay Intertechnology, Inc. hereby certifies that all its products that are identified as Halogen-Free follow Halogen-Free requirements as per JEDEC JS709A standards. Please note that some Vishay documentation may still make reference to the IEC 61249-2-21 definition. We confirm that all the products identified as being compliant to IEC 61249-2-21 conform to JEDEC JS709A standards.