Terminal Boards for Motion Control

For Mitsubishi Servos

DIN-812M0

Terminal Board for Mitsubishi MR-J2S-A Servo Amplifiers

- On-board Connector Type: 100-pin SCSI-II
- Dimensions:
  123 mm x 107 mm x 44 mm (W x L x H)
- Mating Cable:
  -ACL-102100-1: 100-pin SCSI-II cable, 1 M

DIN-814M0

Terminal Board for Mitsubishi MR-J2S-A Servo Amplifiers

- On-board Connector Type: 100-pin SCSI-II
- Dimensions:
  123 mm x 107 mm x 44 mm (W x L x H)
- Mating Cable:
  -ACL-102100-1: 100-pin SCSI-II cable, 1 M

DIN-68M-J2A0



Terminal Board for Mitsubishi MR-J2S-A Servo Amplifiers

- On-board Connector Type: 68-pin SCSI-II
- Dimensions:
  103 mm x 83 mm x 43 mm (W x L x H)
- Mating Cable:
  -ACL-10568-1: 68-pin SCSI-VHDCI cable, 1 M
  -ACL-10569-1: 68-pin SCSI-II cable, 1 M

DIN-814M-J3A0

Terminal Board for Mitsubishi MR-J3S-A Servo Amplifiers

- Onboard Connector Type: 100-pin SCSI-II
- Dimensions:
  123 mm x 107 mm x 44 mm (W x L x H)
- Mating Cable:
  -ACL-102100-1: 100-pin SCSI-II cable, 1 M

For Mitsubishi Servos

DIN-68M-J3A0

Terminal Board for Mitsubishi MR-J3S-A Servo Amplifiers

- On-board Connector Type: 68-pin SCSI-II
- Dimensions:
  103 mm x 83 mm x 43 mm (W x L x H)
- Mating Cables:
  - ACL-10568-1: 68-pin SCSI-VHDCI cable, 1 M
  - ACL-10569-1: 68-pin SCSI-II cable, 1 M

DIN-839-J3B



Terminal Board for Mitsubishi MR-J2S-A Servo Amplifiers

- On-board Connector Type: 68-pin SCSI-II
- Dimensions:
  103 mm x 83 mm x 43 mm (W x L x H)
- Mating Cable:
  - MA-J2HBUS M: controller to amplifier bus cable

DIN-825-J3A



Terminal Board for Mitsubishi MR-J3S-A Servo Amplifiers

- On-board Connector Type: 68-pin SCSI-II
- Dimensions:
  103 mm x 83 mm x 43 mm (W x L x H)
- Mating Cable:
  -ACL-10568-1: 68-pin SCSI-VHDCI cable, 1 M
  -ACL-10569-1: 68-pin SCSI-II cable, 1 M

For Yaskawa Servos

DIN-814Y0

Terminal Board for Yaskawa Sigma II/III/V Servo Amplifiers

- On-board Connector Type: 100-pin SCSI-II
- Dimensions:
  123 mm x 107 mm x 44 mm (W x L x H)
- Mating Cable:
  - ACL-102100-1: 100-pin SCSI-II cable, 1 M

DIN-68Y-SGII0

Terminal Board for Yaskawa Sigma II/III/V Servo Amplifiers

- On-board Connector Type: 68-pin SCSI-II
- Dimensions:
  103 mm x 83 mm x 43 mm (W x L x H)
- Mating Cables:
  -ACL-10568-1: 68-pin SCSI-VHDCI cable, 1 M
  -ACL-10569-1: 68-pin SCSI-II cable, 1 M

For Panasonic Servos

DIN-814P-A40



Terminal Board for Panasonic MINAS A4 Servo Amplifiers with 100-pin SCSI-II connector

- On-board Connector Type: 100-pin SCSI-II
- Dimensions: 123 mm x 107 mm x 44 mm (W x L x H)
- Mating Cable:
  - ACL-102100-1: 100-pin SCSI-II cable, 1 M

DIN-68P-A40



Terminal Board for Panasonic MINAS A4 Servo Amplifiers with 68-pin SCSI-II connector

- On-board Connector Type: 68-pin SCSI-II
- Supports 500 k & 2 Mpps pulse frequency input options
- Mating Cables:
  - ACL-10568-1: 68-pin SCSI-VHDCI cable, 1 M
  - ACL-10569-1: 68-pin SCSI-II cable, 1 M

DIN-814PA0

Terminal Board for Panasonic MINAS A Servo Amplifiers

- On-board Connector Type: 100-pin SCSI-II
- Dimensions: 123 mm x 107 mm x 44 mm (W x L x H)
- Mating Cable:
  - ACL-102100-1: 100-pin SCSI-II cable, 1 M